

Fingertip Pulse Oximeter



SPECIFICATION

- SpO2 Measurement Range: 70% ~ 100%
- SpO2 Measurement Accuracy: 70% ~ 100% $\pm$ 2%; 0% ~ 69% unspecified
- PR Measurement Range: 25bpm ~ 250bpm
- PR Measurement Accuracy: 25bpm ~ 250bpm $\pm$ 3bpm, resolution 1bpm
- OLED Display with an SpO2, Pulse Rate, Pulse Bar, and Waveform Monitor
- Automatic Switch-Off Feature
- Compact and Lightweight
- Six Display Modes and Adjustable Brightness
- 2 AAA Batteries

Operation Temperature: 41°F ~ 104°F
Storage Temperature: -40°F ~ 140°F
Operation Humidity: 10% ~ 95% no condensation
Storage Humidity: 10% ~ 95% no condensation



www.medsourcelabs.com

Item #	Description	U of M
MS-74002	Fingertip Pulse Oximeter w/SpO2, PR & Pulse Bar and Waveform	EA